

AE-P32-28



DIP28/PLCC32 specialized adapter for EPROM/FLASH with open top socket.

Click the programmer model below to get an appropriate list of the devices supported by the adapter:

- [ChipProg+](#)
- [ChipProg-40](#)
- [ChipProg-48, ChipProg-G4](#)

Adapter analogues supplied by third-party vendors:

Logical Systems: PA32-28

Adapter Wiring Diagram:

| DIP-28 | PLCC-32 |
|--------|---------|
| 1 | 2 |
| 2 | 3 |
| 3 | 4 |
| 4 | 5 |
| 5 | 6 |
| 6 | 7 |
| 7 | 8 |
| 8 | 9 |
| 9 | 10 |
| 10 | 11 |
| 11 | 13 |
| 12 | 14 |

| | |
|----|----|
| 13 | 15 |
| 14 | 16 |
| 15 | 18 |
| 16 | 19 |
| 17 | 20 |
| 18 | 21 |
| 19 | 22 |
| 20 | 23 |
| 21 | 24 |
| 22 | 25 |
| 23 | 27 |
| 24 | 28 |
| 25 | 29 |
| 26 | 30 |
| 27 | 31 |
| 28 | 32 |